


| JKL PART NUMBER | VOLTAGE CIRCUIT | BREAK-DOWN | NOMINAL AMPERAGE | SERIES RESISTOR (OHMS) | LIFE HOURS AVERAGE |
|-----------------|-----------------|------------|------------------|------------------------|--------------------|
| A1G | 105-125 | 65 VAC | .0007 | 100K | 25,000 |
| A1G-R | 105-125 | 65 VAC | .0007 | *100K | 25,000 |

ORANGE GLOW

*BUILT-IN RESISTOR PROVIDED

| | | | | | |
|--|---|-----------------------------------|-------------------|--------------------------|--|
| METRIC  THIRD ANGLE PROJECTION | DIMENSIONS ARE IN MILLIMETERS TOLERANCE UNLESS OTHERWISE SPECIFIED 1 PL +/- 0.2 2 PL +/- 0.20 ANGLE +/- | JKL COMPONENTS CORPORATION | | | |
| | TITLE NEON T-1 3/4 STANDARD MIDGET FLANGE LAMP | | | | |
| DRAWN BY L. WENGSTROM | APPVD BY LEW | DATE 11/22/05 | SIZE A | FSCM NO. 55335 | DRAWING NO. NEON T-1 3/4 MIDGET FLANGE |
| - CAD DRAWING - MANUAL REVISIONS NOT PERMITTED | | | SCALE NONE | RELEASED DATE 1/29/01 | REVISION DATE 11/22/05 |
| REV. NO. | DESCRIPTION/ECO NUMBER | APPVD DATE | REV. NO. A | SHEET 1 OF 1 | |

| | | |
|-------------------------------------|---------------------|------------|
| A DRAWING ART TO CAD RELEASED | 11/21/05 1/29/01 | APPVD DATE |
|-------------------------------------|---------------------|------------|